TA-N7/N7B

TA-N7 (Panel: Silver)
AEP Model
UK Model
TA-N7B (Panel: Black)
AEP Model
UK Model
US Model
Canadian Model



TA-N7 (AEP, UK model)

STEREO POWER AMPLIFIER

SPECIFICATIONS

GENERAL

Power Requirements:
240V ac, 50/60Hz (UK model)
220V ac, 50/60Hz (AEP model)
120V ac, 60Hz (US, Canadian model)

Power Consumption:
480W (UK model)
420W (AEP model)
160W (US model)
350VA (Canadian model)

Dimensions:
Approx.
430(W) x 170(h) x 335(d) mm
17(w) x 6¾(h) x 13¼(d) inches
Including projecting parts and controls

Weight:
(UK, AEP model)
Approx. 20.1kg, 44 lb 5 oz (net)
Approx. 22.6kg, 49 lb 14 oz
(with shipping carton)
(US, Canadian model)
Approx. 21kg, 46 lb 5 oz (net)
Approx. 23.6kg, 52 lb 1 oz
(with shipping carton)

—Continued on page 2 —

SAFETY-RELATED COMPONENT WARNING !!

COMPONENTS IDENTIFIED BY SHADING AND ⚠ MARK ON THE SCHEMATIC DIAGRAMS, EXPLODED VIEWS AND IN THE PARTS LIST ARE CRITICAL TO SAFE OPERATION. REPLACE THESE COMPONENTS WITH SONY PARTS WHOSE PART NUMBERS APPEAR AS SHOWN IN THIS MANUAL OR IN SUPPLEMENTS PUBLISHED BY SONY.

ATTENTION AU COMPOSANT AYANT RAPPORT À LA SÉCURITÉ !

LES COMPOSANTS IDENTIFIÉS PAR UN TRAMÉ ET UNE MARQUE ⚠ SUR LES DIAGRAMMES SCHÉMATIQUES, LES VUES EXPLOSÉES ET LA LISTE DES PIÈCES SONT CRITIQUES POUR LA SÉCURITÉ DE FONCTIONNEMENT. NE REMPLACER CES COMPOSANTS QUE PAR DES PIÈCES SONY DONT LES NUMÉROS SONT DONNÉS DANS CE MANUEL OU DES SUPPLÉMENTS PUBLIÉS PAR SONY.

SONY®
SERVICE MANUAL

POWER AMPLIFIER SECTION

Continuous RMS Power Output: (Less than 0.01% THD)
Both channels driven simultaneously
At 20–20,000 Hz
100W + 100W (8Ω)
According to DIN 45500 (AEP, UK model)
100W + 100W (8Ω)

Power Bandwidth: 5–35,000 Hz (8Ω), IHF (AEP, UK model)

Damping Factor: 100 (8Ω, 1kHz)

Harmonic Distortion: Less than 0.01% at rated output
Less than 0.008% at 1W/10W output

Less than 0.01% at 250mW–rated output (US, Canadian model)

IM Distortion: (60Hz: 7kHz = 4:1)
Less than 0.01% at rated output
Less than 0.008% at 1W/10W output

Frequency Response: DC–100,000Hz $^{+0}_{-1}$ dB (DIRECT INPUT)

6–100,000Hz $^{+0}_{-1}$ dB (C COUPLED INPUT)

S/N Ratio: Greater than 120 dB, short-circuited input

Residual Noise: Less than 0.024mV (8Ω) weighting network A

Inputs:

	Sensitivity	Impedance
DIRECT	1.3V (for rated output)	50kΩ
C COUPLED (3Hz cut-off frequency)		

Outputs: SPEAKER terminals:
Accept speakers of 8Ω or more

• MODEL IDENTIFICATIONS

– Specification Label –

AEP model (TA-N7)

SONY
STEREO AMPLIFIER
MODEL NO. TA-N7
AC 220V ~ 50/60Hz 420W
SERIAL NO.
MADE IN

UK model (TA-N7)

SONY
STEREO AMPLIFIER
MODEL NO. TA-N7
AC 240V ~ 50/60Hz 480W
SERIAL NO.
MADE IN

AEP model (TA-N7B)

SONY
STEREO AMPLIFIER
MODEL NO. TA-N7B
AC 220V ~ 50/60Hz 420W
SERIAL NO.
MADE IN

UK model (TA-N7B)

SONY
STEREO AMPLIFIER
MODEL NO. TA-N7B
AC 240V ~ 50/60Hz 480W
SERIAL NO.
MADE IN

US model (TA-N7B)

SONY
STEREO AMPLIFIER
MODEL NO. TA-N7B
AC 120V 60Hz 160W
SERIAL NO.
MADE IN

Canadian model (TA-N7B)

SONY
STEREO AMPLIFIER
MODEL NO. TA-N7B
AC 120V 60Hz 350VA
SERIAL NO.
MADE IN

SERVICING NOTES

- This set uses bipolar transistors and V-FETs in cascade circuit to maintain stable biasing. When replacing the three P-channel V-FETs 2SK60 and/or the three N-channel V-FETs 2SJ18 in each channel, use three matched ones which have the same Vp (pinch-off voltage)-rank figure printed on them as shown below. The fluctuation of the Vp rank of the three can be acceptable on one-rank-difference basis.



- Two kinds of hexagonal-socket screwdrivers are required for the following removal.



SECTION 1
OUTLINE

1-1. BLOCK DIAGRAM



SECTION 2
DISASSEMBLY

Remove the parts in the numerical order.

FRONT PANEL REMOVAL



BOTTOM PLATE AND HEAT SINK REMOVAL



SECTION 3
ADJUSTMENT

Note:

1. Apply the rated ac line voltage to the set directly. Do not increase the voltage gradually by using a variable transformer or other such instrument; this will cause a V-FET failure.
2. Turn the set on and wait a few minutes for warm-up.
3. Alternately repeat the two adjustments 2 or 3 times.

DC Balance Adjustment

Adjust RV101(L-CH) and RV201 (R-CH) for 0V dc with no signal input.





DC Bias Adjustment

Adjust RV102 (L-CH) and RV202 (R-CH) for 30–70 mV dc with no signal input.



SECTION 4
DIAGRAMS

A B C D

4-1. MOUNTING DIAGRAM – L-CH Power Amp Board –

– Conductor Side –

- **Replacement Semiconductors: See page 8.**



Q	111 108	107 106	162 168	131	166 167	105	147 146	145 144 130	103	101	165 164	109 104	161	163	151 153 110	102	152 154
D				133 131			130 162		161	132	151 152	101			102		154

- : B + pattern
- : nonflammable resistor
- : fusible resistor.

A B C

4-2. MOUNTING DIAGRAM – R-CH Power Amp Board –

– Conductor Side –

- **Replacement Semiconductors: See page 8.**



Q	501 502	252 254	251 253 202	210	204	263 209	261 264 201	265	203	245 244 230	247 246	205	266, 267	231	262 268	207 206	211 208
D		254	202			201	251 252	232	261		230 262			233 231			

- : B+pattern
- : B – pattern
- : nonflammable resistor
- : fusible resistor.



• Replacement Semiconductors

For replacement, use semiconductors except in ( ).

Q101, 102, 144, 147, 166, 167, 201, 202, 244, 247, 266, 267 : 2SA678



Q103, 104, 203, 204 : 2SK30A



Q105, 205: 2SK97



Q109, 209: 2SA639S



Q110, 210 : 2SA896



Q106–108, 206–208 : 2SC926A



Q145, 146, 151–154, 245, 246, 251–254, 164, 165, 264, 265, 501, 502 : 2SC1364



(2SC634A)



Q111, 130, 211, 230 : 2SC 1962



Q131, 231: 2SA835



Q132–134, 232–234 : 2SK60



Q135–137, 235–237 : 2SC1173
Q163, 263 : 2SC1061



Q138–140, 238–240 : 2SA473
Q168, 268 : 2SA671



Q141–143, 241–243 : 2SJ18



Q161, 162, 261, 262 : 2SK42-2



D101, 102, 201, 202 : MV12N



D103, 203: SV04S (SV04F)



D130–133, 230–233 : 1S1555

D151, 152, 251, 252, 351–354, 451–454 : 10E2

D154, 254: 1T22AM (1T22A)



D161, 162, 261, 262 : EQB01-11Z



D301, 401: S5VB20



4-4. MOUNTING DIAGRAM — L-CH Power Amp Board —

— Component Side —

Note.

- [redacted] : B + pattern
- [redacted]
- —→— : signal path
- ▲ : nonflammable resistor
- Ⓕ : fusible resistor.

- Voltages are dc with respect to ground unless otherwise noted.
- Readings are taken under no signal conditions with a VOM (20kΩ/V).
  ( ) : voltage variations according to the rank of V-FET.

power amp (R-CH)



D	452 451 401 454 453 — 301 351 352 353 354

Q	111 108 — 107 106 — 162 168 131 — 167 166 105 — 146 147 — 144 145 130 — 103 — 101 — 164 165
D	131 133 — 162 130 — 161 — 132 — 152 151

Socket Board Installation





D	452 451 454 453 401 301 351 352 353 354

Q	111 108 106 107 168 162 131 167 166 105 146 147 130 144 145 103 101 164 165 109 104 161 163 102 110 153 151 154 152 137 134 143 140 136 133 142 139 135 132 141 138	Q
D	131 133 162 130 161 132 152 151 101 102 154 103	D

4-5. MOUNTING DIAGRAM – R-CH Power Amp Board –

– Component Side –

- **Replacement Semiconductors: See page 8.**

- : B + pattern

- ●— ➤ —: signal path
- ▲ : nonflammable resistor.
- Ⓕ : fusible resistor.

- Voltages are dc with respect to ground unless otherwise noted.
- Readings are taken under no signal conditions with a VOM (20kΩ/V).
  ( ) : voltage variations according to the rank of V-FET.



Socket Board Installation



Q	237	234 243	240	236	233 242	239	235	232 241	238	502 501	254 252	210 202 253 251		204	209 263	261	201 264	265	203	230 244 245	246 247	205	267 266	231	268 262	206 207	208	211	Q
D					203							254	202		201	252 251		232	261		262 230			231 233					D

TA-N7/N7B



235	232 241	238	502 501	254 252	210 202 253 251	204	209 263	261	201 264	265	203	230 244 245	246 247	205	267 266	231	268 262	206 207	208 211	Q
				254	202		201	252 251		232	261		262 230			231 233				D

D	452 451 454 453	401
	301	351 352 353 354

Note: The components identified by shading and ⚠ mark are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par un tramé et une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

4-6. SCHEMATIC DIAGRAM



mposants identifiés par un tramé et une marque ⚠ ritiques pour la sécurité. Ne les remplacer que par ièce portant le numéro spécifié.



- All capacitors are in μF unless otherwise noted. pF=μμF 50 WV or less are not indicated except for electrolytics.
- All resistors are in ohms ½W unless otherwise noted. kΩ = 1000Ω, MΩ = 1000kΩ
- ▭: nonflammable resistor.
- ▭: fusible resistor.
- ——: B+ bus.
- – – –: B–bus.
- ▭: panel designation.
- ▭: adjustment for repair.
- Voltages are dc with respect to ground unless otherwise noted.
- Readings are taken under no signal conditions with a VOM (20kΩ/V).
  ( ) : voltage variations according to the rank of V-FET.
- Switch

Ref. No.	Switch	Position
S501	POWER	OFF

5-1.

Note:

- Items with no part number and/or no description are not stocked because they are seldom required for routine service.
- All screws are Phillips (cross recess) type unless otherwise noted.
  (–) = slotted head
- Circled letters (Ⓐ to Ⓩ) are applicable to European models only.



5-2.

Note:

- Items with no part number and/or no description are not stocked because they are seldom required for routine service.
- All screws are Phillips (cross recess) type unless otherwise noted.
  (–) = slotted head
- Circled letters (Ⓐ to Ⓩ) are applicable to European models only.



Note: The components identified by shading and ⚠ mark are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par un tramé et une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

5-3.

SECTION 5
EXPLODED VIEWS

Note:

- Items with no part number and/or no description are not stocked because they are seldom required for routine service.
- All screws are Phillips (cross recess) type unless otherwise noted.
  (–) = slotted head
- Circled letters (Ⓐ to Ⓩ) are applicable to European models only.



Note: The components identified by shading and ⚠ mark are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par un tramé et une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

Note:

- Items with no part number and/or no description are not stocked because they are seldom required for routine service.
- All screws are Phillips (cross recess) type unless otherwise noted.
  (–) = slotted head
- Circled letters (Ⓐ to Ⓩ) are applicable to European models only.



Note: The components identified by shading and ⚠ mark are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par un tramé et une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

5-4.



Note: The components identified by shading and ⚠ mark are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par un tramé et une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

SECTION 6
ELECTRICAL PARTS LIST

• Circled letters (Ⓐ to Ⓩ) are applicable to European models only.

Ref. No.	*Part No.*	*Description*
		SEMICONDUCTORS
		Transistors
Q101, 201 Q102, 202	8-727-788-00	Ⓒ 2SA678
Q103, 203 Q104, 204	8-729-203-04	Ⓑ 2SK30A
Q105, 205	8-765-342-10	Ⓕ 2SK97
Q106–108 Q206–208	8-720-950-03	Ⓓ 2SC926A
Q109, 209	8-729-163-93	Ⓒ 2SA639S
Q110, 210	8-765-082-20	Ⓒ 2SA896
Q111, 211 Q130, 230	8-765-170-01	Ⓔ 2SC1962
Q131, 231	8-762-020-00	Ⓔ 2SA835
Q132–134 Q232–234	8-762-355-00	Ⓙ 2SK60
Q135–137 Q235–237	8-729-217-33	Ⓒ 2SC1173
Q138–140 Q238–240	8-729-247-33	Ⓒ 2SA473
Q141–143 Q241–243	8-762-455-00	Ⓚ 2SJ18
Q144, 244	8-727-788-00	Ⓒ 2SA678
⇒ Q145, 245 ⇒ Q146, 246	8-729-663-47	Ⓑ 2SC1364
Q147, 247	8-727-788-00	Ⓒ 2SA678
⇒ Q151–154 ⇒ Q251–254	8-729-663-47	Ⓔ 2SC1364
Q161, 261 Q162, 262	8-727-312-00	Ⓒ 2SK42-2
Q163, 263	8-729-316-12	Ⓓ 2SC1061
⇒ Q164, 264 ⇒ Q165, 265	8-729-663-47	Ⓑ 2SC1364
Q166, 266 Q167, 267	8-727-788-00	Ⓒ 2SA678
Q168, 268	8-729-317-12	Ⓔ 2SA671
⇒ Q501, 502	8-729-663-47	Ⓑ 2SC1364

Ref. No.	*Part No.*	*Description*
		Diodes
D101, 201 D102, 202	8-719-912-00	Ⓑ MV12N
⇒ D103, 203	8-719-300-11	Ⓒ SV04S
D130–133 D230–233	8-719-815-55	Ⓑ 1S1555
D151, 251	⚠ 8-719-200-02	Ⓑ 10E2
D152, 252	8-719-200-02	Ⓑ 10E2
⇒ D154, 254	8-719-422-21	Ⓑ 1T22AM
D161, 261 D162, 262	8-719-930-11	Ⓑ EQB01-11Z
D301, 401	⚠ 8-719-505-20	Ⓕ S5VB20
D351–354 D451–454	⚠ 8-719-200-02	Ⓑ 10E2
		Thermistor
PTH 151 PTH 251	1-800-427-00	Ⓑ positive

CAPACITORS

All capacitors are in μF and ceramic unless otherwise noted.
50WV or less are not indicated except for electrolytics. pF = μμF, elect = electrolytic

C101, 201	1-130-083-11	Ⓒ	1	100V	polyethylene
C102, 202	1-103-775-11	Ⓐ	0.001		polystyrol
C103, 203	1-102-947-11	Ⓐ	10p		
C104, 204	1-103-775-11	Ⓐ	0.001		polystyrol
C106, 206	1-102-963-11	Ⓐ	33p		
C107, 207	1-102-947-11	Ⓐ	10p		
C108, 208	1-108-239-12	Ⓐ	0.01		mylar
C109, 209	1-131-217-11	Ⓑ	2.2	35V	tantalum
C110, 210 C111, 211	1-108-234-12	Ⓐ	0.0047		mylar
C112, 212	1-102-947-11	Ⓐ	10p		
C130, 230 C131, 231	1-123-187-11	Ⓐ	10	25V	elect
C132, 232 C133, 233	1-108-239-12	Ⓐ	0.01		mylar

• ⇒: Due to standardization, interchangeable replacements may be substituted for parts specified in the diagrams.

Note: The components identified by shading and ⚠ mark are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par un tramé et une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

• Circled letters (Ⓐ to Ⓩ) are applicable to European models only.

Ref. No.	Part No.		Description		
C134, 234	1-108-244-12	Ⓐ	0.033		mylar
C135–140, C235–240	1-108-847-12	Ⓐ	0.068		mylar
C141, 241	1-103-755-11	Ⓐ	150p		polystyrol
C142, 242	1-108-246-12	Ⓐ	0.047		mylar
C151, 251	1-123-081-11	Ⓑ	22	100V	elect
C152, 252	1-123-072-11	Ⓑ	220	10V	elect
C153, 253	1-123-196-11	Ⓐ	100	10V	elect
C162, 262, C163, 263	1-123-255-11	Ⓑ	4.7	100V	elect
C165, 265, C166, 266	1-121-423-11	Ⓑ	220	50V	elect
C301, 401	⚠1-125-151-11	Ⓠ	22000+22000	71V	elect
C303, 403, C304, 404	1-123-262-11	Ⓔ	1000	63V	elect
C305, 405, C306, 406	⚠1-130-084-11	Ⓓ	2.2	100V	polyethylene
C307, 407	1-121-479-11	Ⓐ	22	16V	elect
C501	1-123-195-11	Ⓐ	47	10V	elect

RESISTORS

All resistors are in ohms and ½W carbon unless otherwise noted.

R101, 201	1-244-914-11	Ⓐ	51k		
R102, 202	1-244-873-11	Ⓐ	1k		
R103, 203	1-244-913-11	Ⓐ	47k		
R104, 204	1-244-921-11	Ⓐ	100k		
R105, 205	1-244-873-11	Ⓐ	1k		
R106, 206	1-244-881-11	Ⓐ	2.2k		
R107, 207	1-244-893-11	Ⓐ	6.8k		
R108, 208	1-244-873-11	Ⓐ	1k		
R109, 209	1-244-921-11	Ⓐ	100k		
R110, 210	1-244-913-11	Ⓐ	47k		
R111, 211	1-244-856-11	Ⓐ	200		
R112, 212	1-244-925-11	Ⓐ	150k		
R113, 213	1-244-889-11	Ⓐ	4.7k		
R114, 214	1-244-897-11	Ⓐ	10k		
R115, 215	1-244-873-11	Ⓐ	1k		
R116, 216	1-244-897-11	Ⓐ	10k		
R117, 217	1-244-905-11	Ⓐ	22k		
R118, 218	1-244-882-11	Ⓐ	2.4k		
R119, 219	1-244-905-11	Ⓐ	22k		
R120, 220, R121, 221	⚠1-212-889-11	Ⓐ	220	¼W	fusible
R122, 222	⚠1-212-873-11	Ⓐ	47	¼W	fusible
R123, 223, R124, 224	1-244-897-11	Ⓐ	10k		
R125, 225	⚠1-212-889-11	Ⓐ	220	¼W	fusible
R126, 226	1-244-921-11	Ⓐ	100k		
R127, 227	⚠1-212-950-11	Ⓐ	4.7	½W	fusible
R128, 228	1-244-633-11	Ⓐ	22	¼W	
R130, 230, R131, 231	1-244-897-11	Ⓐ	10k		
R132, 232, R133, 233	1-244-881-11	Ⓐ	2.2k		
R134, 234	⚠1-212-982-11	Ⓐ	100	½W	fusible
R135, 235	⚠1-212-990-11	Ⓐ	220	½W	fusible
R136, 236	⚠1-212-982-11	Ⓐ	100	½W	fusible
R137–139, R237–239	⚠1-212-893-11	Ⓐ	330	¼W	fusible
R140–145, R240–245	1-217-158-11	Ⓐ	0.47	5W	metal oxide
R146–148, R246–248	⚠1-212-893-11	Ⓐ	330	¼W	fusible
R149, 249, R150, 250	1-206-459-11	Ⓐ	6.8	2W	metal oxide
R151, 251	1-244-913-11	Ⓐ	47k		
R152, 252	1-244-885-11	Ⓐ	3.3k		
R153, 253	⚠1-206-657-11	Ⓐ	510	2W	metal oxide
R154, 254	1-244-915-11	Ⓐ	56k		
R155, 255	1-244-857-11	Ⓐ	220		
R161, 261	⚠1-212-857-11	Ⓐ	10	¼W	fusible
R162, 262	1-244-853-11	Ⓐ	150		
R163, 263	1-244-891-11	Ⓐ	5.6k		
R164, 264	1-244-885-11	Ⓐ	3.3k		
R165, 265	1-244-890-11	Ⓐ	5.1k		
R166, 266	⚠1-212-857-11	Ⓐ	10	¼W	fusible
R167, 267	1-244-853-11	Ⓐ	150		
R168, 268, R169, 269	1-244-873-11	Ⓐ	1k		
R301, 401	1-244-910-11	Ⓐ	36k		
R501, 502	⚠1-217-160-11	Ⓑ	1	5W	metal oxide
R503	1-244-718-11		75k	¼W	(US, Canadian model)
	1-244-925-11	Ⓐ	120k		(AEP, UK model)
R504, 505	1-244-906-11	Ⓐ	24k		
R506	1-244-909-11	Ⓐ	33k		
R507	1-244-873-11	Ⓐ	1k		
RV101, 201	1-224-247-XX	Ⓒ	100		adjustable, DC balance
RV102, 202	1-224-253-XX	Ⓒ	22k		adjustable, DC bias

SWITCH

S501	⚠1-552-141-12	Ⓔ	Pushbutton, POWER (AEP, UK model)
	⚠1-552-246-11		Pushbutton, POWER (US, Canadian model)

MISCELLANEOUS

CB301, 401	⚠1-532-523-11		Circuit Breaker, 4A (US, Canadian model)
	⚠1-532-531-11	Ⓒ	Circuit Breaker, 2A (AEP, UK model)
CNP501	1-509-546-00	Ⓓ	Socket, 3p AC IN (AEP, UK model)
	1-551-421-11		Cord, power (US, Canadian model)
CP301, 303, CP401, 403	⚠1-102-355-11	Ⓑ	Encapsulated Component
CR501	⚠1-231-326-11		Encapsulated Component (US model)
	⚠1-231-341-00		Encapsulated Component (Canadian model)
F501	⚠1-532-496-00	Ⓒ	Fuse, 109°C, 10A
J101, 201, J102, 202	1-507-378-21	Ⓑ	Jack, 2p; C-COUPLED, DIRECT
L131, 231	1-420-879-00	Ⓑ	Coil, 3.3μH
NL501	⚠1-519-139-00	Ⓑ	Neon Lamp, power
PT101, 201	⚠1-442-971-00		Transformer, power (US, Canadian model)
	⚠1-442-973-00	Ⓥ	Transformer, power (AEP, UK model)
PT102, 202	⚠1-442-970-00		Transformer, power (US, Canadian model)
	⚠1-442-972-00	Ⓞ	Transformer, power (AEP, UK model)
RY151, 251	1-515-293-00	Ⓗ	Relay
RY501	1-515-278-00	Ⓕ	Relay
TM131	1-535-195-21	Ⓕ	Terminal Strip 2p; LEFT SPEAKER
TM231	1-535-195-31	Ⓕ	Terminal Strip 2p; RIGHT SPEAKER
	1-525-186-00	Ⓑ	Socket, transistor
	1-536-392-XX	Ⓑ	Terminal, lug

• Circled letters (Ⓐ to Ⓩ) are applicable to European models only.

ACCESSORIES & PACKING MATERIALS

Part No.		Description
⚠1-534-819-12	Ⓖ	Cord, power (UK model)
3-701-622-00	Ⓐ	Bag, plastic (UK model)
3-701-630-00	Ⓐ	Bag, plastic; printed matters
3-770-058-21		Manual, instruction (US model)
3-770-058-21, 3-794-245-31		Manual, instruction (Canadian model)
3-770-441-11	Ⓗ	Manual, instruction (AEP, UK model)
4-848-648-00	Ⓑ	Bag, protection; set
4-849-622-00	Ⓒ	Cushion (A)
4-849-623-00	Ⓒ	Cushion (B)
4-849-637-00	Ⓕ	Carton (TA-N7)
4-849-638-00	Ⓒ	Spacer
4-849-639-00	Ⓒ	Cushion, lower
4-849-643-00	Ⓖ	Carton (TA-N7B)

Note: The components identified by shading and ⚠ mark are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par un tramé et une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

Note: The components identified by shading and ⚠ mark are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par un tramé et une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

9-958-445-12

Sony Corporation

78D0297-1
Printed in Japan